



Meinberg Radio Clocks

Lange Wand 9
31812 Bad Pyrmont, Germany
Phone: +49 (5281) 9309-0
Fax: +49 (5281) 9309-30
<https://www.meinbergglobal.com>
info@meinberg.de

GPS180: GPS Satellite Receiver with LC-Display and Control Elements (Eurocard)

The variety of inputs/outputs makes this GPS receiver the first choice for a broad range of applications, including time and frequency synchronization tasks and the measurement of asynchronous time events.

Key Features

- Pulses per second and per minute
- 2 time trigger inputs
- 2 RS-232 interfaces
- Alarm output
- DDS frequency synthesizer
- DCF77-simulation
- Meinberg GPS Antenna/Converter Unit connected with up to 300m of standard coaxial cable RG58
- DC-insulated antenna circuit
- Standard frequency outputs
- Flash-EPROM with bootstrap loader
- Optional up to 4 serial ports 4 programmable switching outputs timecode generator (IRIG-B, AFNOR) 5 MHz Frequency Output
- Including GPS antenna, 20m standard cable and manual on USB key

Description

The frequency locking of the master oscillator to the GPS system enables the module GPS180 to generate fixed and programmable standard frequencies with very high accuracy and stability. Various oscillator options allow to meet different requirements concerning the accuracy of the outputs in the most cost efficient way.

The pulse generator of GPS180 generates pulses per second and per minute. Four programmable outputs are available. The pulses are synchronized to UTC second.

Up to four serial interfaces are available for sending time strings. These ASCII telegrams include information regarding time, date and status of the GPS receiver.

The module provides two inputs for measurement of asynchronous time events. These capture events are shown on the LC-Display and can be read via a serial interface.

The front panel integrates a LC-Display that shows information regarding the GPS receiver in different menus. In combination with four push buttons it is also used to setup all configurable parameters.

Characteristics

Receiver Type	12 channel GPS C/A-code receiver
Type of antenna	Remote powered [1] GPS antenna/converter unit , up to 300m distance to antenna with RG58 and up to 700m distance with RG213 cable
Display	LC display, 4 x 16 characters
Cable type	Coaxial cable RG58 indoor or outdoor usage (BNC-, N-Norm-connector)
Status Info	Fail-LED shows that the internal timing has not been synchronized or that a system error occurred Lock-LED shows that the calculation of the position has been achieved after reset
Synchronization Time	Max. 1 minute in normal operation mode, approx. 12 minutes after a cold start (discharged buffer battery)
Frequency Outputs	10 MHz, 1 MHz, 100 KHz or (optional) 5MHz, TTL level Synthesizer 1/8 Hz up to 10 MHz (TTL level, sine wave 1.5Veff, open drain) Accuracy: $\pm 1 \cdot 10^{-9}$ (timebase OCXO LQ), GPS-synchronous for more than 20 minutes Different oscillators available, look at [2] oscillator options
Pulse outputs	Pulse per second (PPS) and pulse per minute (PPM). TTL level, pulse width: 200msec
Accuracy of Pulse Outputs	Depends on oscillator option: < ± 50 ns (OCXO SQ, OCXO MQ, OCXO HQ, OCXO DHQ, Rubidium)
Interface	Two independent serial RS-232-interfaces, menu configurable
Data format of interfaces	Baud rate: 300, 600, 1200, 2400, 4800, 9600, 19200 Baud Data format: 7E1, 7E2, 7N2, 7O1, 7O2, 8E1, 8N1, 8N2, 8O1 Time telegram: [3] Meinberg Standard Time String , SAT, Uni Erlangen (NTP), SPA, Sysplex, RACAL, NMEA0183 (RMC,GGA,ZDA), Meinberg GPS, COMPUTIME, ION oder [4] Capture String

DCF77 emulation	DCF77-emulation, TTL-level
Switch outputs	<p>Optional: Four TTL outputs can configured independently for the following modes: - free programmable cyclic or fixed impulses - timecode - timer mode; three 'ON'- and three 'OFF'-states can be setup per day The switch states can be inverted for all three outputs, the impulse lengths are configurable in 10msec steps in a range from 10msec to 10sec. The impulse output can be configured for all channels together to 'always' or 'ifsync'.</p>
Generated time codes	<p>IRIG B002: 100pps, DCLS signal, no carrier, BCD time of year IRIG B122: 100pps, AM sine wave signal, 1 kHz carrier, BCD time of year IRIG B003: 100pps, DCLS signal, no carrier, BCD time of year, SBS time of day IRIG B123: 100pps, AM sine wave signal, 1kHz carrier, BCD time of year, SBS time of day IRIG B006: 100 pps, DCLS Signal, no carrier, BCD time-of-year, Year IRIG B126: 100 pps, AM sine wave signal, 1 kHz carrier frequency, BCD time-of-year, Year IRIG B007: 100 pps, DCLS Signal, no carrier, BCD time-of-year, Year, SBS time-of-day IRIG B127: 100 pps, AM sine wave signal, 1 kHz carrier frequency, BCD time-of-year, Year, SBS time-of-day IEEE1344: Code according to IEEE1344-1995, 100pps, AM sine wave signal, 1kHz carrier, BCD time of year, SBS time of day, IEEE1344 expansion for date, time zone, daylight saving and leap second in Control Funktionen Segment C37.118: Like IEEE1344 - with turned sign bit for UTC-Offset AFNOR: Code according to NFS-87500, 100pps, AM sine wave signal, 1kHz carrier, BCD time of year, complete date, SBS time of day</p>
Time-Trigger inputs	Resolution: 100 nsec, triggered by falling TTL slope Time of trigger event readable via RS232-interface
Alarm output	Synchronous state of the module, TTL high level if synchronous
Dimensions of the front panel	21HP/3U (106mm x 128mm), with integrated membrane keyboard
Electrical connectors	96-pin DIN 41612 connector
Antenna Connector	BNC-connector
Power Supply	+5V DC
Backup battery type	<p>CR2032 - button cell lithium battery When main power supply fails, hardware clock runs free on quartz basis, almanac data is stored in RAM Life time of lithium battery min. 10 years</p>
Firmware	Flash-EPROM, bootstrap loader

Current Draw	+5V 1.1 A to 1.4 A (depending on oscillator type)
Board type	Eurocard
Ambient Temperature	0 ... 50 °C / 32 ... 122 °F
Humidity	Max. 85 %
Warranty	Three-year warranty
RoHS Status of Product	This product is fully RoHS-compliant.
WEEE Status of Product	This product is handled as a B2B category product. For disposal, it must be returned to the manufacturer to ensure WEEE compliance. Any transportation expenses for returning this product (at end-of-life) must be covered by the end user, while Meinberg will cover the costs for the waste disposal itself.

Manual

The English manual is available as a PDF file: [5][Download \(PDF\)](#)

Links:

[1] <https://www.meinbergglobal.com/english/products/gps-antenna-converter.htm>

[2] <https://www.meinbergglobal.com/english/products/specs/gpsopt.htm>

[3] <https://www.meinbergglobal.com/english/specs/timestr.htm>

[4] <https://www.meinbergglobal.com/english/specs/capstr.htm>

[5] <https://www.meinbergglobal.com/download/docs/manuals/english/gps180.pdf>