


KEW 2003A

- Equipped to measure both AC and DC current with transformer jaws of large diameter.
- Can measure AC and DC currents up to 2000A.
- Output terminal for connection to recorders.



| | |
|--------------------|---|
| AC A | 400A/2000A |
| AC V | 400/750V |
| DC A | 400/2000A |
| DC V | 400/1000V |
| Ω | 400/4000Ω |
| Continuity buzzer | buzzer sounds below 50±35Ω |
| Output | Recorder :DC400mV against AC/DC400A DC200mV against AC/DC2000A |
| Conductor Size | Ø55mm max. |
| Safety Standard | IEC 61010-1 CAT.IV 600V CAT.III 1000V IEC 61010-031 IEC 61010-2-032 |
| Frequency Response | 40Hz~1kHz |
| Withstand Voltage | 6880V AC for 5 seconds |
| Power Source | R6P (AA) (1.5V) ×2 |
| Dimensions | 250(L) × 105(W) × 49(D)mm |
| Weight | 530g approx. |
| Accessories | 7107 (Test Leads) 8201 (Output Plug) 9094 (Carrying Case) R6P (AA) × 2 Instruction Manual |
| Optional | 8008 (Multi-Tran) (AC only) 7014 (Output Cord) |

Contact:

Industrial Supply Syndicate

54, Ezra Street, Kolkata- 700 001, INDIA

Phone: 22350923, 22356676 Fax: +91 33 30222923

Email: info@industrialindia.com Website: www.industrialindia.com